

SDM630MCT40mA Smart Meter

DIN Rail Energy Meter for Single and Three Phase Electrical Systems

- ▶ Measures kWh kVArh, kW, kVAr, kVA, P, F, PF, Hz, dmd, V, A, THD, etc.
- ▶ Bi-directional measurement IMP & EXP
- ▶ Two pulse outputs
- ▶ RS-485 Modbus
- ▶ Din rail mounting 35mm
- ▶ 40 mA CT connection
- ▶ Better than Class 1 / B accuracy



MODEL	SDM630MCT40mA
Measurement Accuracy	
Type of Measurement	RMS including harmonics on three phase AC system (3P,3P+N)
Power	0.5% of range maximum
Active Energy	IEC 62053 - 22 Class 0.5S, IEC 62053 - 21 Class 1.0
Reactive Energy	IEC 62053-23 Class 2
Frequency	0.2% of mid-frequency
Current	0.5% of range maximum
Voltage	0.5% of range maximum
Power Factor	1% of unity (0.01)
Input	
CT Secondary / Primary	40 mA / 120 A
Rated Voltage (Un)	380 / 400 V a.c.
Operating Voltage Range	173 to 480 V a.c. (L-L)
Communications	
Communication Protocol	Modbus RTU
Communication Address	1 ~ 247
Transmission Distance	1000 m Maximum
Transmission Speed	1200 bps ~ 38400 bps
Parity	None (default), Odd, Even
Stop Bits	1
Response Time	< 100 ms

* SDM630MCT40mA smart meter is recommended to be used along with residential string inverters and ESS hybrid inverters.

** It has included three 120A/40mA Current Transformers. For system larger than 80 kW, users need to purchase larger capacity CT that meets the following requirements:

1. The selected CT's primary rating should be larger than the maximum current passing through the system's AC busbar.
2. Maximum Current = system capacity / 230 / 3

*** Please consult Kstar for more details.

